

E.T DC BLUE DIGITAL GDO LIMITS

- 1 Door must be engaged in the middle position
- 2 Power on
- 3 Press/Hold SET Bt for +/- 3 Sec
Both SET led and OPEN led will illuminate
- 4 Press/Hold OPEN button until door is in the OPEN position
- 5 Press/Release SET button to confirm
- 6 Press/Hold CLOSE button until door is in the CLOSED position
- 7 Press/Release SET button to confirm
- 8 Door will run OPEN and then CLOSED to confirm limit setup.

E.T DC BLUE DIGITAL SENSIVITY

- 1 Using the dipswitches, select one of the following:
- 2 **Light Resistance**
Dipswitch 2 ON and 3 OFF
- 3 **Light-Medium Resistance**
Dipswitch 2 OFF and 3 OFF
- 4 **Medium-Heavy Resistance**
Dipswitch 2 OFF and 3 ON
- 5 **Heavy Resistance**
Dipswitch 2 ON and 3 ON

E.T DC BLUE DIGITAL AUTOCLOSE

- 1 To activate AUTOCLOSE, switch Dipswitch 1 ON
- 2 Adjust the AUTOCLOSE TIME by turning the autoclose pod CLOCKWISE
- 3 Pod can be adjusted from 1 sec to 100 sec

E.T DC BLUE DIGITAL REMOTE PROG

- 1 Press/Hold TX button
 - 2 While holding TX button, Press/Release LEARN button
 - 3 LEARN led will flash to confirm successful
 - 4 Repeat above steps for additional remotes
- Master Erase**
- 1 Power down
 - 2 Press/Hold LEARN button
 - 3 While holding LEARN button, apply power
 - 4 LEARN led will begin to flash
 - 5 LEARN led will go off
 - 6 LEARN led will illuminate permanently
 - 7 Release LEARN button and remove power